

Technical data

UCP320D1

High precision angular contact ball bearings

INDUSTRY CALCUL FACTORS

Equivalent dynamic radial load

$$P = X.F_r + Y.F_a$$

Series			e	Single or DT bearing arrangement				DB or DF arrangement			
				Fa / Fr ≤ e		Fa / Fr > e		Fa / Fr ≤ e		Fa / Fr > e	
				X	Y	X	Y	X	Y	X	Y
70 (NTN & SNR) 72 (NTN & SNR) 78 (NTN) 79 (NTN) 719 (SNR)	15°	0.178	0.38	1	0	0.44	1.47	1	1.65	0.72	2.39
		0.357	0.4				1.4		1.57		2.28
		0.714	0.43				1.3		1.46		2.11
		1.07	0.46				1.23		1.38		2
		1.43	0.47				1.19		1.34		1.93
		2.14	0.5				1.12		1.26		1.82
		3.57	0.55				1.02		1.14		1.66
		5.35	0.56						1.12		1.63
		7.14	0.56				1		1.12		1.63
	25°		0.68			0.41	0.87		0.92	0.67	1.41
	30°		0.8			0.39	0.76		0.78	0.63	1.24

Equivalent static radial load

$$P_o = X_o.F_r + Y_o.F_a$$

Series		Single or DT bearing arrangement		DB or DF arrangement		
		X ₀	Y ₀	X ₀	Y ₀	
70 (NTN & SNR)	15°	0.5	0.46	1	0.92	
72 (NTN & SNR)			0.38		0.76	
78 (NTN)	0.33					0.66
79 (NTN)						
719 (SNR)	30°					

For single or DT bearing arrangement :

If $P_o < F_r$, then use $P_o = F_r$