

Stopper Cylinder / Fixed Mounting Height

Series RSQ

ø12, ø16, ø20, ø32, ø40, ø50

How to Order

Standard RSQ **B** **20** - **15** **D** -

With auto switch RSDQ **B** **20** - **15** **D** - **M9BW** -

Mounting bracket

With auto switch
(Built-in magnet)

B Through-hole (Standard)
A Both ends tapped style

Note 1) Since ø12 uses a common tube for both A and B, only B is used for part no. denotation.

Bore size

12	12 mm
16	16 mm
20	20 mm
32	32 mm
40	40 mm
50	50 mm

Port thread type

Nil	M thread	ø12, ø16
TN	Rc	ø20 to ø50
TF	NPT	
F	G	
Built-in One-touch fittings (2)		

Note 2) Bore sizes available w/ One-touch fittings are ø20 to ø50.
Note 3) TF for ø20 indicates M5.

Cylinder stroke (mm)

12	10
16	10, 15
20	10, 15, 20
32	10, 15, 20
40	20, 25, 30
50	20, 25, 30

Auto switch

Nil Without auto switch

* For the applicable auto switch model, refer to the table below.

Made to Order Specifications
For details, refer to page 1374.

Number of auto switches

Nil	2 pcs.
S	1 pc.

Rod end configuration

Symbol	Configuration	Application
Nil	Round bar type	—
K	Chamfered type	—
R	Roller type	—
L	Lever type (Non-adjustable) (4)	Basic style
B	Lever type (4) (Energy absorbing Adjustable deformation)	—
C		With cancel cap
D		With lock mechanism
E		With lock & cancel

Note 4) The lever types are applicable only to bore sizes ø32, ø40 and ø50.

Action

D	Double acting
B	Double acting with spring loaded
T	Single acting (Spring extend)

Built-in Magnet Cylinder Model

If a built-in magnet cylinder without an auto switch is required, there is no need to enter the symbol for the auto switch.

(Example) RSDQB32-15D

Applicable Auto Switch/Refer to pages 1719 to 1827 for further information on auto switches.

Type	Special function	Electrical entry	Indicator light	Wiring (Output)	Load voltage		Auto switch model				Lead wire length (m)					Pre-wired connector	Applicable load					
					DC	AC	Perpendicular		In-line		0.5 (Nil)	1 (M)	3 (L)	5 (Z)	None (N)							
							ø12	ø16, ø20, ø32 to ø50	ø12	ø16, ø20, ø32 to ø50												
Solid state switch	—	Grommet	Yes	3-wire (NPN)	24 V	5 V, 12 V	—	M9NV		M9N		●	●	●	○	—	○	IC circuit	Relay, PLC			
		3-wire (PNP)		M9PV		M9P		●	●	●	○	—	○									
	Connector	2-wire		M9BV		M9B		●	●	●	○	—	○	—								
		—		J79C		—		●	—	●	●	●	—									
	Diagnostic indication (2-color indication)	Grommet		3-wire (NPN)		5 V, 12 V		M9N WV		M9N W		●	●	●	○	—	○	IC circuit				
				3-wire (PNP)		12 V		M9P WV		M9P W		●	●	●	○	—	○					
	2-wire			12 V		M9B WV		M9B W		●	●	●	○	—	○	—						
	3-wire (NPN)			5 V, 12 V		M9N AV		M9N A		○	○	●	○	—	○		IC circuit					
	3-wire (PNP)			12 V		M9P AV		M9P A		○	○	●	○	—	○							
	2-wire			12 V		M9B AV		M9B A		○	○	●	○	—	○	—						
4-wire	5 V, 12 V		—		—		F79F	●	—	●	○	—	○	IC circuit								
Reed switch	—		Grommet	Yes	3-wire (NPN equivalent)	—	5V	—	A96V		A96		●	—	●	—	—	—	IC circuit	Relay, PLC		
		—					200 V		A72		A72H		●	—	●	—	—	—	—			
		Connector					24 V		12 V	100 V	A93V		A93		●	—	●	—	—		—	—
									5 V, 12 V	100 V or less	A90V		A90		●	—	●	—	—		—	IC circuit
	12 V		—		A73C			—		●	—	●	●	●	—	—						
	5 V, 12 V		24 V or less		A80C			—		●	—	●	●	●	—	IC circuit						
	Diagnostic indication (2-color indication)	Grommet	Yes		No	Yes	No	Yes	No	Yes	No	Yes	No	Yes	No	Yes	No	—				
	—		Grommet		Yes	No	Yes	No	Yes	No	Yes	No	Yes	No	Yes	No	—					
—																						

* Lead wire length symbols: 0.5 m Nil (Example) M9NW
1 m M (Example) M9NWM
3 m L (Example) M9NWL
5 m Z (Example) M9NWZ
None N (Example) J79CN

* Solid state auto switches marked with "○" are produced upon receipt of order.

* Since there are other applicable auto switches than listed, refer to page 1386 for details.

* For details about auto switches with pre-wired connector, refer to pages 1784 and 1785.

* When D-A9□(V)/M9□(V)/M9□W(V)/M9□A(V)L types with ø32 to ø50 are mounted on a side other than the port side, order auto switch mounting brackets separately. Refer to page 1386 for details.