


## Manifold Exploded View

### Type 60P (Flat ribbon cable) manifold

### Type 60S (Plug-in, EX180 Serial wiring) manifold

### Type 60G (Plug-in, PC wiring with power supply terminal) manifold



### Component Parts / Plug-in

No.	Description		Part no.	Note
1	SUP/EXH block assembly	Internal pilot	SJ3000-50-1A-□□	(Metric size) C6: With ø6 one-touch fitting (straight) C8: With ø8 one-touch fitting (straight) L6: With ø6 one-touch fitting (elbow upward entry) L8: With ø8 one-touch fitting (elbow upward entry) B6: With ø6 one-touch fitting (elbow downward entry) B8: With ø8 one-touch fitting (elbow downward entry)
		Internal pilot / Built-in silencer	SJ3000-50-1AS-□□	
		External pilot	SJ3000-50-1AR-□□ (X, PE port: Metric size ø4 Inch size ø5/32")	
		External pilot / Built-in silencer	SJ3000-50-1ARS-□□ (X port: Metric size ø4 Inch size ø5/32")	(Inch size) N7: With 1/4" one-touch fitting (straight) N9: With 5/16" one-touch fitting (straight)
		For different pressures, internal pilot <sup>Note 1)</sup>	SJ3000-50-3A-□□	
		For different pressures <sup>Note 1)</sup> Internal pilot / Built-in silencer	SJ3000-50-3AS-□□	
2	End block assembly		SJ3000-53-1A	For U side
3	Connector block assembly		SJ3000-42-□A-□ SJ3000-76-2A-□	Refer to the connector block assembly part no. shown below.
4	DIN rail		VZ1000-11-1-□	Refer to page 61.
5	SI unit		EX180-□□	Refer to the SI unit part numbers on page 34.
6	End block assembly		SJ3000-53-2A	For D side

Note 1) The valves cannot be operated only with the SUP/EXH block assembly for different pressure, select them in combination with the SUP/EXH block assembly for internal/external pilot.

Note 2) Refer to page 60 about the SUP/EXH block disk assembly and method of handling of parts at different pressures.

### Connector Block Assembly Part No.

Connector specifications	Mounting position	Part no.	Note
For D-sub connector	D side	SJ3000-42-1A-□	□: 1 (Connector upward) □: 2 (Connector lateral)
For flat ribbon cable 26 pins		SJ3000-42-2A-□	
For flat ribbon cable 20 pins		SJ3000-42-3A-□	
For flat ribbon cable 10 pins		SJ3000-42-4A-□	
For PC wiring 20 pins		SJ3000-42-6A-□	
For EX180 serial wiring <sup>Note)</sup>		SJ3000-42-5A	
For PC wiring 20 pins with power supply terminal		SJ3000-76-2A-05	

Note) SI unit is not included.