

How to Order Replacement Parts for Single Unit

Valve assembly

ZK2 - VA **A** **K** **5** **L** A - **□** - A

1 2 3 4 5

► p. 43 Construction ⑤

① Applicable system

A	Ejector system
P	Vacuum pump system

③ Rated voltage

5	24 VDC
6	12 VDC

② Valve type

K	Supply valve: N.C., Release valve: N.C.
J	Supply valve: N.C., Release valve: None
R	Supply valve: Self-holding release valve linked, Release valve: N.C.
E*1	Supply valve: N.O., Release valve: N.C.

*1 When "P" is selected for ①, the "E" type cannot be selected.

④ Wiring

C	Manifold common wiring
L	Individual wiring: With connector assembly (Lead wire length: 300 mm)
LO	Individual wiring: Without connector assembly

⑤ Other specifications

C	Vacuum pump system (Valve type R) PE port female thread specification (M3)
—	Specifications other than that listed above

* Select the ZK2-VAA□LOA-A for a switch with energy saving function.

Connector assembly

ZK2 - LV **W** **□** - A


► p. 43 Construction ⑥

Applicable valve type

W	Valve type K/R/E
S	Valve type J

Lead wire length

—	300 mm
6	600 mm
10	1000 mm
20	2000 mm
30	3000 mm



One-touch fitting assembly (Purchasing order is available in units of 10 pieces.)

KJH **06** - C2

► p. 43 Construction ⑦

Port size

06	Ø 6 One-touch fitting	Metric size
07	Ø 1/4" One-touch fitting	Inch size

Sound absorbing material (10 pcs. per set)

► p. 43 Construction ⑧

ZK2 - SE1 - **1** - A

Sound absorbing material hole diameter

1	300 µm
---	--------

Vacuum port adapter assembly (Purchasing order is available in units of 1 piece.)

ZK2 - VA1S **8** - A

► p. 43 Construction ⑨

One-touch fitting size

6	Ø 6 One-touch fitting	Metric size
8	Ø 8 One-touch fitting	Metric size
7	Ø 1/4" One-touch fitting	Inch size
9	Ø 5/16" One-touch fitting	Inch size

Filter element (10 pcs. per set)

► p. 43 Construction ⑩

ZK2 - FE1 - **3** - A

Nominal filtration rating

3	30 µm
---	-------

Body gasket*1 (10 pcs. per set)

► p. 43 Construction ⑪

ZK2 - BG5 - **1** - A

Applicable type

1	One check valve type (All specifications other than vacuum switch with energy saving function and exhaust interference prevention valve)
2	Two check valve type (Vacuum switch with energy saving function and exhaust interference prevention valve)

*1 When ZK2-BG5-2-A is mounted, the workpiece cannot be removed until vacuum is released.

Filter case*1

► p. 43 Construction ⑫

ZK2 - FC **□** - A

Port for the pressure switch or sensor

Symbol	Port for the pressure switch or sensor	Filter case colour
P	With port (type with pressure switch or sensor)	Opaque
T	Without port (type without pressure switch or sensor)	Clear

*1 Vacuum port adapter assembly is not included.